
LED Tape COB-4



22601035901 06.07.2020

Montage- und Bedienungsanleitung

Hera LED Linienleuchte
Typ LED Tape COB-4

Bestimmungsgemäße Verwendung

Selbstklebende, flexible LED Streifen ohne Punktoptik. Als Möbelleuchte gemäß VDE 0710 Teil 14/04.82 zum Einbau in Möbel zugelassen.

1. **Beim Austausch von defekten Teilen dürfen nur Originalteile verwendet werden.**
2. **Alle Steckverbindungen immer bis zum Anschlag einführen.**
3. **Polung beachten (Aufdruck auf LED Tape)!**
4. **Die Lichtquelle dieser Leuchte ist nicht ersetzbar; wenn die Lichtquelle ihr Lebensdauerende erreicht hat, ist die gesamte Leuchte zu ersetzen.**
5. **Die Leuchte nicht demontieren da das Licht der Leuchtdioden das menschliche Auge verletzen kann.**
6. **Anschluß nur an spezielle LED - Konverter Hera Typ LED 24/...W mit konstanter Ausgangsspannung 24 V DC, max. 25 W bzw. 5 m pro Anschlussleitung (nur bei angelöteter Anschlussleitung).**
7. **Da es bei höheren Leistungen zu Spannungsabfällen und daraus resultierenden Lichtstärkeunterschieden zwischen dem Anfang und dem Ende eines Streifen kommen kann, sollten bei Lichtbändern diese immer „Anfang an Anfang" und „Ende an Ende" zusammen montiert werden.**
8. **Werden andere als die angegebenen LED - Konverter eingesetzt, übernimmt Hera keine Gewährleistung.**
9. **Für trockene, saubere, hochenergetische Oberflächen (keine pulverlackierten Bleche) geeignet. Weitere Verarbeitungshinweise auf der Produktseite unter www.hera-online.de.**

A **erhältliches Zubehör:**

Anschlussleitung zum Anlöten

Entsorgen Sie elektrische Geräte nicht im Hausmüll, nutzen Sie die Sammelstellen in Ihrer Gemeinde. Wenn Sie das Gerät durch ein neues ersetzen, ist der Verkäufer gesetzlich verpflichtet, das alte mindestens kostenlos zur Entsorgung entgegenzunehmen.

Nachdruck auch auszugsweise verboten.
Erklärung der Symbole: http://www.hera-online.de/de/fachliches.html

Assembly and operating Instructions

Hera LED Linear Luminaire
Type LED Tape COB-4

Intended use

Self-adhesive, flexible LED strips without visible luminous spots. Approved as a furniture luminaire in accordance with VDE 0710 part 14/04.82 for installation in furniture.

1. **Faulty parts should only be replaced with original parts.**
2. **Always fully insert all plug connections.**
3. **Observe the correct polarity (print on LED Tape)!**
4. **The light source of this luminaire is not replaceable; when the light source reaches its end of life the whole luminaire must be replaced.**
5. **Do not disassemble the luminaire as the light diode can cause damage to the eyes.**
6. **Connection only to special LED - Converter Hera Type LED 24/...W with a constant output voltage 24 V DC, maximum 25 W or 5 m per supply cable (only with supply cable solder on tape).**
7. **A high output within one light strip can lead to voltage drop and can cause differences in the light-output between the beginning and the end of the light strip. In this case - for the use of several light strips in one light row - please mount "the beginning together with the beginning" and "the end together with the end".**
8. **Hera grants no warranty when other LED converters as the prescribed converters are used.**
9. **Suitable for dry, clean, high-level surfaces (no powder coated sheets).**

A **available accessories:**

supply cable for soldering

Do not dispose of electrical appliances in household waste, use separate collection facilities. When replacing old appliances with new ones, the retailer is obliged by law to accept to take back your old appliance for disposal free of charge.

Reproduction of this document in whole or part is forbidden.
Explanation of the Symbols: http://www.hera-online.de/en/technical-information.html

Hera®
Hera GmbH & Co. KG
Dieselstraße 9
32130 Enger / Germany

STORELIGHTS®

Blankensteinstraße 34-36
32257 Bünde
Tel. 0 52 23 / 18 35 70
Fax 0 52 23 / 57 23
info@storelights.de
www.storelights.de

Ein Service von
Storelights.de
-Ihre helle Freude-